

ZPA INMAT 51/66

ZPA INMAT 51/66 communication protocol

[Supported device types and versions](#)

[Communication line configuration](#)

[Communication station configuration](#)

[Station protocol parameters](#)

[I/O tag configuration](#)

[Literature](#)

[Changes and modifications](#)

[Document revisions](#)

Supported device types and versions

This protocol supports data reading and writing to the dataloggers INMAT 66 and INMAT 51 produced by ZPA Nová Paka (Czech republic).

Communication line configuration

- Communication line category: [Serial](#), [SerialOverUDP Device Redundant](#).
- The parameters of asynchronous line are set according to version and type of device connection:
 - the settings from manufacturer (you can find out it on a display in the control menu): 9600 Baud, 8 data bits, even parity, 1 stop bit.

Note:

When testing, we found out that there was a short period between sending the request and receiving the response (less than 10 ms). You should enter the similar values (1 to 10 ms) into the parameter "Receive delay" in line mode. If there are several devices on one line (RS485), you should set such value which is suitable for all devices to ensure 100% success of data transfer.

Communication station configuration

- Communication protocol: **ZPA INMAT 51/66**.
- The station address is a decimal number in the range of 0 up to 126 (you can find it on a display of device).
- When necessary, you may enable the synchronization of real-time on station – INMAT devices.

Station protocol parameters

[Communication station - configuration dialog box](#) - tab **Protocol parameters**.

They influence some of the optional parameters. You can set the following station protocol parameters:

Table 1

Parameter	Meaning	Unit	Default value
Wait Timeout	Delay between reading the response until it is completed.	ms	200 millisec.
Wait First Timeout	First waiting for response after sending the request.	ms	200 millisec.
Retry Timeout	Delay between the response retry if some error in communication occurs.	ms	500 millisec.
Max Wait Retry	Maximum retries of reading the response until it is completed.	-	4
Retry Count	Number of response retries if some error in communication occurs.	-	2
Local Source Address	Local source address of D2000 KOM process.	-	0
Full Debug	Communication monitoring high level, information about reading I/O tags and received values are displayed.		NO

I/O tag configuration

I/O tags: **Ai**

For address, you must set two parameters:

INX and **IY**

These address parameters are provided by the producer (ZPA Nová Paka) when buying the device.

The values are in hexadecimal format:

- INX – 0 up to FF
- IY – 0 up to FF

Literature

Changes and modifications

- 21.1.2000 – Testing the communication

Document revisions

- Ver. 1.1 – February 8, 2000 – Updating
- Ver. 1.2 – November 21, 2010 – Updating



Related pages:

[Communication protocols](#)