

TimeSynchroStation

Declaration

```
unsigned int _stdcall TimeSynchroStation(struct StationPar * St)
```

Parameters

St	Pointer to StationPar structure.
----	--

Description

The function **TimeSynchroStation** (_TimeSynchroStation@4 in the Stdcall calling convention) is optional. It is called (or not called) according to the station polling parameter "[Period](#)". The task of the function is to synchronize the real time of the device.

Return code

Code	Description
RQ_OK	The request has been executed.
RQ_ERROR	An error occurred (the device does not communicate or is out of service, or there is any error), the station changes into the status COM_ERR or HARD_ERR after returning from the function.
RQ_IGNORED	The function was ignored and the station status is not changed.



Related pages:

[D2000 KomAPI - interface functions](#)