## Representation of Data from the Log Database (Work with D2000 HI)

## Representation of data from the log database

Clicking on the OK button in the dialog box System Logging - Settings opens the following window displaying data from the log database according to defined parameters.

		1/1 (18) 🔻	<u> </u>	🔹 Mask:	×			
Name	Description	Event rising time	User	Old value	New value	Priority	Incident	Log type
SystemError	Informácia o syst	3/4/2010 3:00:0				Critical alarm	TimeChannel CK	ALR
🗂 aaa.HIP	New Process	3/5/2010 2:42:1	Disconn	Run	Stop	Information		PRC
🗂 ws1phum1.C	New Process	3/5/2010 2:42:3	Disconn	Run	Stop	Information		PRC
ws1pbre1.CNF	New Process	3/5/2010 2:44:2	Disconn	Run	Stop	Information		PRC
ws1pbre1.CNF	New Process	3/5/2010 2:44:3	Connect	Stop	Run	Information	TCP/IP Client IP	PRC
ws1pbre1.CNF	New Process	3/5/2010 2:44:3	SystemD	Run	Run	Warning	TCP/IP Client IP	PRC
SV.STM_Ev		3/5/2010 2:47:1	SystemD			Information	Modification	SYS
SV.STM_Ev		3/5/2010 2:49:0	SystemD			Information	Modification	SYS
E.Test_CNT		3/5/2010 2:50:1	SystemD			Information	Modification	SYS
🐉 E.Test_CNT		3/5/2010 2:50:1	SystemD			Information	Modification	SYS
🐉 E. Test_CNT		3/5/2010 2:50:3	SystemD			Information	Modification	SYS
🗂 ws1pbre1_HI	New Process	3/5/2010 2:51:5	Disconn	Run	Stop	Information		PRC
ws1pbre1.HIP	New Process	3/5/2010 2:51:5	Disconn	Run	Stop	Information		PRC
•								•
ws1pbre1.HIP	New Process	3/5/2010 2:52:0	Connect	Stop	Bun	Information	TCP/IP Client IP	PRC
🖉 ws1pbre1.HIP	New Process	3/5/2010 2:52:2	SystemD	Run	Bun	Warning	TCP/IP Client IP	PRC
ws1pbre1_HI	New Process	3/5/2010 2:52:4	ws1pbre	Stop	Bun	Information	TCP/IP Client IP	PRC
WS1GOND1	New Process	3/5/2010 2:55:2	Connect	Stop	Bun	Information	TCP/IP Client IP	PRC
🌽 WS1GOND1	New Process	3/5/2010 2:55:3	SystemD	Run	Run	Warning	TCP/IP Client IP	PRC

	Table columns configuration.
	System logging - settings.
	Save the table data to a file. After clicking the icon, the menu will appear allowing you to save data to a text file, CSV file or to the clipboard. It is also possible to save either all data of the table ( <b>All data</b> item) or only selected data (lines).
	Go to the beginning of the table (the first table page).
	Go to the previous page of the table.
1/6 (101)	Information about the displayed table - current table page / total number of pages (number of table lines).
	Go to the next page of the table.
	Go to the end of the table (to the last page of the table).
Y	Blocks the mask and shows the filter for selection. Text entered into the mask will not be deleted.
*	Deletes the text in the filter. The button is active if the text is written in the filter.

Mask Selection mask to display data in the table - it is applied to the columns **Name** (in the format \*..\* AND/OR \*..\*) and/or **Description** (in the format \* AND/OR \*..\*). For more information see the topic Defining a mask.

Graphic symbols of event types. Pointing the mouse cursor at a particular symbol displays the name of the event type that the symbol represents.

Here are described the columns of the table (list).

Column	Meaning				
Name	D2000 System object name concerning the given event + the graphic symbol showing a group of logged events.				
Description	Description of the event.				
Event rising time	Date and time of the event rise. If the <b>msec</b> option is enabled then the column displays time data with milliseconds accuracy.				
User	Name of operator logged in the system when the event occurred (for processes - this column shows "Connect" or "Disconnect").				
	<ul> <li>Connect - the process is connected to the process Server</li> <li>Disconnect - the process is disconnected from the process Server</li> </ul>				
Old value	Value of object before the event arose.				
Incident	Cause of the logged event.				
	In case of event type *LOG* New value *Logon* - the logon of user contains:				
	<ul> <li>process name, through which the user has logged on - required,</li> </ul>				
	<ul> <li>list of present hardware keys, providing that they are detected,</li> <li>IP address of the client, providing that the connection was done through the Windows Terminal Services (Remote Desktop) or Citrix MetaFrame.</li> </ul>				
	Example:				
	NB1.CNF[ 480,R][ 917]WTS:172.16.1.134 The user has logged on to NB1.CNF via Remote Desktop from the workstation with IP=172.16.1.134. The workstation had the HW key with the unique identifier = 480. The server, where the process run physically, had the HW key with the unique identifier = 917.				
Priority	Priority (significance) indicates the event's importance. The system supports five priority levels (in order from the lowest priority to the highest one):				
	Information				
	Warning     Alarm				
	Critical alarm				
	• Error				
Log type	Type of the logged event:				
	• ALR - Alarms				
	SYS - System     PRC - Processes				
	• KOM - Kom				
	<ul> <li>OPR - Operator's interventions</li> <li>EVT - Events</li> </ul>				
	LOG - Logon / Logoff     MAN - Manual intervention				
	CHV - Spontaneous value change				
	• TIM - Time logger				

Double-click on a line in the table (list) will open the information window, containing well-arranged information about the particular line from the table. This presentation is suitable in case the particular line contains too much information that cannot be completely displayed in a single line. The window contains the buttons to move in the table (list).

In the list there is the possibility to sort data according to the **Event rising time** column. New values are added on the last page for upward sorting and for downward sorting on the first page of the list.

## Note

• In case the displayed time interval is floating, the table is horizontally divided into two parts. The lower part comprises the last five events. This feature is applicable for the Last hour, Last 8 hours, Last 12 hours and Last 24 hours radio buttons in the System Logging - Settings dialog box. The table is not divided only in case of defined time interval- the Exactly radio button.

## Filter usage

Y Click on button activates the filter and the mask is blocked whereas the text, written in the mask, is not deleted.

The condition defining the relation between columns Name and Description displays instead of the mask.

- AND the condition from both columns
- OR the condition from the column Name or Description, eventually from both one

🗉 Logging: Ascending - Last 24 hour									
		1/1 (15) 🗨	•	*		Name AND OR Des	script		-
Name	Description	Event rising time	User	Old value	New value	Priority	Incident	Log type	-
w* 7	Enter text here 🏼 🍸	Enter text here 🏼 🍸	Enter 🍸	Enter text 🍸	Enter text 🍸	Information,Warnin 🍸	Enter text here 🏼 🍸	ALR,SYS,P	
ws1phum1.C	New Process	3/5/2010 2:42:3	Disconn	Bun	Stop	Information		PRC	
📰 ws1pbre1.CNF	New Process	3/5/2010 2:44:2	Disconn	Run	Stop	Information		PRC	
📰 ws1pbre1.CNF	New Process	3/5/2010 2:44:3	Connect	Stop	Run	Information	TCP/IP Client IP	PRC	
😗 ws1pbre1.CNF	New Process	3/5/2010 2:44:3	SystemD	Run	Run	Warning	TCP/IP Client IP	PRC	=
🗂 ws1pbre1_HI	New Process	3/5/2010 2:51:5	Disconn	Run	Stop	Information		PRC	

The filter works similarly to a mask, i.e. text can be written into a field.

The columns Priority and Log type are an exception. Text cannot be written into a filter of these columns but items are chosen from the drop-down list Y.

Priority	Incident	Log type		
Information,Warnin 🖙	· Cutastanthana 🖘			
Information	Information	Information		
Information	Warning			
Information	Alarm			
Warning	Critical alarm			
Information				
Information	Error			
17 8	TOD ID OF LUD	DDC .		

after pushing the button placed close to text field

In the column, the Log type user can choose more items.

Log type	Old value Nev
PRC	ALR
PRC	SYS
PRC	PRC
PRC	ком
PRC	
PRC	OPR
PRC	EVT
PRC	LOG
PRC	MAN
PRC	1
PRC	CHV
PRC	TIM

If the priority or log type is entered incorrectly, the following window with a message appears:



The changes in the filter will be shown also in dialog box System Logging - Settings.

Text from the filter is deleted after clicking on button is active only if the filter contains some text.

